



(Following Paper ID and Roll No. to be filled in your Answer Book)

**PAPER ID : 130402**

Roll No.

--	--	--	--	--	--	--	--	--	--

**B. Tech.**

(SEM. IV) THEORY EXAMINATION, 2014-15

**ELECTRONIC FIELD THEORY**

Time : 2 Hours]

[Total Marks : 50

Note : Attempt all questions.

1 Attempt any four questions : 3.5×4=14

(a) Prove the vector triple product identity

$$A \times B \times C = B(A.C) - C(A.B).$$

(b) What is the physical significance of gradient, divergence and curl.

(c) Evaluate div (curl A) if

$$A = \frac{\sin \phi}{r^2} a_r - \frac{\cos \phi}{r^2} a_r.$$

(d) State Divergence theorem and stokes's theorem.

(e) Express the vector in Cartesian coordinates:

$$A = r^2 \hat{a}_r + \sin \theta \hat{a}_\phi.$$

- (f) Verify the following vector fields are Irrotational and Solenoidal

$$\vec{A} = yz\hat{a}_x + zx\hat{a}_y + xy\hat{a}_z.$$

2 Attempt any two questions : 6×2=12

- (a) Given the potential  $V = \frac{10}{r^2} \sin \theta \cos \phi$ . Find the electric

flux density D at  $(2, \frac{r}{2}, 0)$ .

- (b) Enlist the properties of conductors, dielectrics and semiconductors.

- (c) Derive the expression for capacitance of spherical capacitor using gauss law. A spherical capacitor has radii a= 1.5 cm and b= 4cm has an inhomogeneous

dielectric of  $\epsilon = \frac{10\epsilon_0}{r}$ . Calculate the capacitance of the capacitor.

3 Attempt any two questions : 6×2=12

- (a) State Biot Savarts's law. Prove that the magnetic field due to infinite conductor carrying conductor I at a

distance r is  $H = \frac{I}{2\pi r}$ .

- (b) State and explain Maxwell's equations. Discuss its physical significance.

- (c) Derive an expression for energy in magnetic field.

4 Attempt any two questions : 6×2=12

- (a) Derive the expression of reflection and transmission coefficients. Derive the relation between two.
- (b) State and Explain Poynting theorem.
- (c) A uniform plane wave propagating in medium has

$$E = 2e^{-az} \sin(10^8 t - \beta z) a_y \text{ V/m.}$$

If a medium is characterized by  $\epsilon_r = 2$ ,  $\mu_r = 10$  and  $\sigma = 5 \text{ S/m}$ . Find :

- (i) Attenuation constant
  - (ii) Phase constant
  - (iii) Velocity of propagation
  - (iv) Propagation constant
  - (v) Intrinsic impedance.
-